



GPP-1326/2323/3323/4323

FEATURES

- 4.3" TFT LCD Display
- Supports Setting Value, Measurement Value and Output Waveform Display
- Load Function (CC, CV, CR Mode)
- Setting Resolution: 1mV/0.1mA ; Read Back Resolution: 0.1mV/0.1mA
- Low Ripple Noise: $\leq 350\mu\text{Vrms}/\leq 2\text{mArms}$
- Transient Response Time: $\leq 50\mu\text{s}$
- Tracking Series and Parallel Function without Additional External Wiring
- Utilizing Hardware to Realize Over Voltage Protection/Over Current Protection/Over Temperature Protection
- Delay Function/Output Monitoring Function/Output Recorder Function
- Intelligent Temperature Control Fan Effectively Reduces Noise
- Sequential Output Function and Built-in 8 Template Waveforms
- The Output Recorder Function Records The Output Voltage & Current Parameters with A Minimum Recording Interval of 1 Second
- Provides 10 Sets of Memory for Each Sequence/Delay/Recorder/Panel Setting Condition
- GPP-3323 Supports A USB(Type A)Output Terminal
- Standard: RS-232, USB, Ext I/O ; Optional (Manufacturer Installed Only) : LAN, GPIB+LAN
- Compatible with Commands of GPD-X303S Series



Front Panel



Rear Panel

APPLICATIONS

- School and Research Institute
- Energy Storage Device Industry
- Semiconductor Industry
- Consumer Electronics Industry

With the maximum output power of 217W, the GPP-Series, the multi-channel programmable DC power supply, includes four models: GPP-1326 (0~32V/0~6A) for single-channel output and GPP-2323 for dual-channel output (CH1:0~32V/0~3A, CH2:0~32V/0~3A), GPP-3323 for three-channel output (CH1:0~32V/0~3A, CH2:0~32V/0~3A, CH3:1.8V, 2.5V, 3.3V, 5.0V/5A) and GPP-4323 for four-channel output (CH1:0~32V/0~3A, CH2:0~32V/0~3A, CH3:0~5V/0~1A, CH4:0~15V/0~1A). This series not only provides high program resolution (1mV/0.1mA) and read back resolution (0.1mV/0.1mA), but also features optimal low-ripple noise characteristics $\leq 350\mu\text{Vrms}/\leq 2\text{mArms}$ and output transient recovery capability $\leq 50\mu\text{s}$. Independent output on-off switch is provided for each channel.

For series and parallel applications of CH1 and CH2, the tracking function of the GPP-Series utilizes the internal circuit to automatically switch the output to serial or parallel output without additional external wiring, providing users with convenience not only in operating procedures but also a more stable output. The tracking function design of other brands requires additional external wiring connections for the output in series or parallel. However, excessively long, thin or inconsistent external wiring may cause inaccurate voltage or current output.

The GPP-Series offers a variety of display modes, including single or multi-channel setting values, measurement values, and waveform displays. The Monitor function of the GPP-Series allows users to set monitoring conditions according to requirements, sound alarms or stop output during the measurement process, and stop measurement and protect the customer's DUT. The GPP-Series provides output recorder function, which records the voltage/current of the output process to the internal memory, and the result can be stored as a (*.REC) or (*.CSV) file, which can then be transferred to the USB flash drive. The stored *.CSV can be exported to the Excel to conduct the future analysis.

The CH1/CH2 of the GPP-Series are designed with the load function. A single power supply can set one channel as the power output, and one channel for the load function to consume the power of the DUT so as to meet the basic charging and discharging test requirements for battery. Channel 1 and channel 2 not only provide 32V/3A power output, but also feature built-in maximum 32V constant voltage load (CV), maximum 3.2A constant current load (CC) and maximum 1k Ω constant resistance load (CR) function.

The GPP-Series provides the sequential output function on Channel 1 and Channel 2. This function not only allows users to edit the power output waveform, but also allows users to set the sequential constant voltage (CV) or constant current (CC) load waveform, i.e. a serial power output or a simulation test of a dynamic load. In order to simplify the setting of waveform editing, the GPP-Series has 8 built-in Template waveforms in the sequence output function for users to directly apply for output, including Sine, Pulse, Ramp, Stair Up, Stair Dn, Stair UpDn, Exp Rise, Exp Fall waveforms.

The sound protection functions include OVP/OCPP/OPP/OTP, in which the protection mechanism for OVP/OCPP/OTP is implemented by hardware circuit that has the advantage of faster response time compared with competitors who adopt software to achieve protections. The OVP/OCPP functions allow users to set the protection action point (except CH3 of GPP-3323) according to the conditions of the DUT. The OPP is only activated during the operation of the load function. The Delay Function sets the length of time during channel 1 or channel 2 power output on or during power output off.

In addition, the Trigger In/Trigger Out functions synchronize external devices. The GPP-3323 channel 3 adds a 3A USB (Type A) output terminal for USB charging test. The intelligent temperature-controlled fan can adjust the speed according to the temperature of the power transistor so as to reduce unnecessary noise. The output value setting and the Sequence/Delay/Recorder functions provide 10 sets of internal memory for use, and can be loaded/stored using a USB flash drive. In addition to the standard RS-232 and USB remote interfaces, the GPP-Series also has an optional LAN or LAN+GPIB interface to facilitate different requirements. The commands of the GPP series conform to SCPI requirements and are compatible with the commands of the GPD-X303S series.

GPP-Series

www.valuetronics.com



GW INSTEK

Simply Reliable

SPECIFICATIONS											
		GPP-4323				GPP-3323			GPP-2323		GPP-1326
OUTPUT MODE	Number of Channel Voltage Current Tracking Series Voltage Tracking Parallel Current	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2	CH1
		0~32V	0~32V	0~5V	0~15V	0~32V	0~32V	1.8/2.5/3.3/5.0V	0~32V	0~32V	0~32V
		0~3A	0~3A	0~1A	0~1A	0~3A	0~3A	5A	0~3A	0~3A	0~6A
		0~64V		—		0~64V		—	0~64V		—
0~6A		0~6A				0~6A					
CONSTANT VOLTAGE OPERATION	Line Regulation	$\leq 0.01\%+3\text{mV}$									
	Load Regulation	$\leq 0.01\%+3\text{mV}$ (rating current $\leq 3\text{A}$); $\leq 0.02\%+5\text{mV}$ (rating current $> 3\text{A}$)									
	Ripple & Noise(5Hz~1MHz)	$\leq 350\mu\text{Vrms}$		$\leq 1\text{mVrms}$		$\leq 350\mu\text{Vrms}$		$\leq 2\text{mVrms}$	$\leq 350\mu\text{Vrms}$		$\leq 500\mu\text{Vrms}$
	Recovery Time	$\leq 50\mu\text{s}$		$\leq 50\mu\text{s}$		$\leq 50\mu\text{s}$		$\leq 100\mu\text{s}$	$\leq 50\mu\text{s}$		$\leq 100\mu\text{s}$
CONSTANT CURRENT OPERATION	Line Regulation	$\leq 0.2\%+3\text{mA}$									
	Load Regulation	$\leq 0.2\%+3\text{mA}$									
	Ripple & Noise	$\leq 2\text{mArms}$				$\leq 2\text{mArms}$			$\leq 2\text{mArms}$		$\leq 4\text{mArms}$
	Voltage	1mV				1mV		—	1mV		1mV
PROGRAMMING RESOLUTION	Current	0.1mA				0.1mA		—	0.1mA		0.2mA
TRACKING OPERATION (CH1,CH2)	Tracking Error	$\leq 0.1\%+10\text{mV}$ of Master(0~32V, No Load, with Load add Load regulation $\leq 100\text{mV}$)									
	Parallel Regulation	Line : $\leq 0.01\%+3\text{mV}$ Load : $\leq 0.01\%+3\text{mV}$ (rating current $\leq 3\text{A}$); $\leq 0.02\%+5\text{mV}$ (rating current $> 3\text{A}$)									
	Series Regulation	Line : $\leq 0.01\%+5\text{mV}$; Load : $\leq 100\text{mV}$									
	Ripple & Noise	$\leq 1\text{mVrms}$, 5Hz ~ 1MHz									
CH3 OPERATION FOR (GPP-3323)	Output Voltage	1.8V/2.5V/3.3V/5.0V, $\pm 5\%$									
	Output Current	5A									
	Line Regulation	$\leq 3\text{mV}$									
	Load Regulation	$\leq 5\text{mV}$									
	Ripple & Noise	2mVrms(5Hz~1MHz)									
	Transient Recovery Time	100 μs									
METER	USB Port Output	1.8V/2.5V/3.3V/5.0V, $\pm 0.35\text{V}$, 3A									
	Voltage Resolution	0.1mV				0.1mV		—	0.1mV		0.1mV
Current Resolution	0.1mA				0.1mA		0.1mA		0.2mA		
Setting Accuracy	$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$				$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$		$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$		$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$		
Readback Accuracy	$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$				$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$		$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$		$\leq \pm(0.03\%+10\text{mV})$ $\leq \pm(0.30\%+10\text{mA})$		
DC LOAD CHARACTERISTIC	Channel	2		—		2		—	2		1
	Display Power	0~50.00W				0~50.00W			0~50.00W		0~100.00W
	Display Voltage	1~33.00V				1~33.00V			1~33.00V		1~33.00V
	Display Current	0~3.200A				0~3.200A			0~3.200A		0~6.200A
	CV Mode Setting Range	1.500V~33.00V				1.500V~33.00V			1.500V~33.00V		1.500V~33.00V
	Resolution	10mV				10mV			10mV		10mV
	Set Accuracy	$\leq 0.1\%+30\text{mV}$				$\leq 0.1\%+30\text{mV}$			$\leq 0.1\%+30\text{mV}$		$\leq 0.1\%+30\text{mV}$
	Read Accuracy	$\leq 0.1\%+30\text{mV}$				$\leq 0.1\%+30\text{mV}$			$\leq 0.1\%+30\text{mV}$		$\leq 0.1\%+30\text{mV}$
	CC Mode Setting Range	0~3.200A				0~3.200A			0~3.200A		0~6.200A
	Resolution	1mA				1mA			1mA		1mA
	Set Accuracy	$\leq 0.3\%+10\text{mA}$				$\leq 0.3\%+10\text{mA}$			$\leq 0.3\%+10\text{mA}$		$\leq 0.3\%+10\text{mA}$
	Read Accuracy	$\leq 0.3\%+10\text{mA}$				$\leq 0.3\%+10\text{mA}$			$\leq 0.3\%+10\text{mA}$		$\leq 0.3\%+10\text{mA}$
	CR Mode Setting Range	1~1k Ω				1~1k Ω			1~1k Ω		1~1k Ω
	Resolution	1 Ω				1 Ω			1 Ω		1 Ω
	Set Accuracy	$\leq 0.3\%+1\Omega$ (Voltage $\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)				$\leq 0.3\%+1\Omega$ (Voltage $\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)			$\leq 0.3\%+1\Omega$ (Voltage $\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)		$\leq 0.3\%+1\Omega$ (Voltage $\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)
	Read Accuracy	$\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)				$\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)			$\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)		$\geq 0.1\text{V}$,and current $\geq 0.1\text{A}$)
INSULATION	Chassis and Terminal Chassis and AC Cord	20M Ω or above (DC 500V) 30M Ω or above (DC 500V)									
ENVIRONMENT CONDITION	Operation Temp	0~40℃									
	Storage Temp	-10~70℃									
	Operating Humidity	$\leq 80\%$ RH									
	Storage Humidity	$\leq 70\%$ RH									
EXTERNAL CONTROL	Yes										
INTERFACE	Std: RS-232/USB(CDC), Opt(Manufacturer installed only): LAN/ GPIB+LAN										
POWER SOURCE	AC100V/120V/220V/230V $\pm 10\%$, 50/60Hz										
DIMENSION & WEIGHT	213 (W) x 145 (H) x 312 (D) mm ; Approx. 7.5kg										

Specifications subject to change without notice. GPP-SeriesGD1DH

ORDERING INFORMATION		ACCESSORIES	
GPP-1326	(32V/6A) Single-Output Programmable DC Power Supply	User Manual x 1 , Power cord x 1	
GPP-2323	(32V/3A*2) Dual-Output Programmable DC Power Supply	GPP-1326 Test Lead GTL-104A x 1, GTL-105A x 1	GPP-2323 Test Lead GTL-104A x 2
GPP-3323	(32V/3A*2; 1.8V or 2.5V or 3.3V or 5V/5A*1) Three-Output Programmable DC Power Supply	GPP-4323 Test Lead GTL-104A x 2, GTL-105A x 2	GPP-3323 Test Lead GTL-104A x 3
GPP-4323	(32V/3A*2; 5V/1A; 15V/1A) Four-Output Programmable DC Power Supply	European Test Leads:	
		GPP-1326 GTL-203A x 1, GTL-204A x 1, GTL-201A x 1	GPP-2323 GTL-204A x 2, GTL-201A x 1
		GPP-4323 GTL-203A x 2, GTL-204A x 2, GTL-201A x 1	GPP-3323 GTL-204A x 3, GTL-201A x 1
OPTIONAL ACCESSORIES			
GTL-246 USB Cable			
OPTIONS (Manufacturer Installed Only)			
LAN Interface; GPIB+LAN Interface			

GOOD WILL INSTRUMENT CO., LTD.
No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan
T +886-2-2268-0389 F +886-2-2268-0639
E-mail: marketing@goodwill.com.tw



www.gwinstek.com



www.facebook.com/GWinstek

GWINSTEK
Simply Reliable