

9710 Series Digital Delay Current Generators

The 9710 Current Pulse Generator is an ideal fire set for airbag squib, detonator and pyrotechnics inititor testing. The instrument provides adjustable current signals up to 25 amps. The unit comes with 2 or 4 digitally controlled load resistant independent outputs. Output pulse widths and delays are unique to each channel and can be precisely controlled from 0.1 to 100 ms in 200 ns steps. The 9710 Current Pulse Generator also provides a TTL Sync output to T0 – particularly useful as a reference source/trigger for cameras or other equipment.

Basic Specifications

- 200 ns Timing Steps
- Up to 25 amps per Channel*
- 2 or 4 Channel Outputs
- Benchtop Design
- Easy Programming Interface
- TTL Sync output to T0
- Safety Interlock



Quantum Composers, Inc. P.O. Box 4248 Bozeman, MT 59772

Phone(406) 582-0227Fax(406) 582-0237Toll Free(800) 510-6530

www.QuantumComposers.com sales@quantumcomposers.com

SPECIFICATIONS

9710 Series

MODELS 9712 - 2 independent channel outputs 9714 - 4 independent channel outputs Standard Communications: RS232 Memory Storage: 12 slots

DELAYS	
channels	independent outputs, with digitally controlled delay and
pulsewidth.	
current	0 to 25 A (bank voltage 44 V minimum)*
resolution	10 mA
accuracy	50 mA
delay	0 to 99.9999998 s
resolution	200 ns
pulse width	100 µs to 100 ms*
resolution	200 ns
accuracy	100 ns + .0001 x delay
timebase	5 MHz, 25 PPM crystal oscillator
RMS jitter	100 ns
trig delay	ext trig to T0, 10 μs
EXTERNAL TRIGGER	
rate	DC to 1/ (75 ms + largest delay + period)
threshold	3 VDC (3 mA into optoisolator)
impedance	1000
NTERNAL RATE GENERATOR	
modes	single shot, external trigger
RMS jitter	100 ns
OUTPUTS(T1,T2)	
impedance	1.405
slew rate	> 2.5 A/µs
overshoot	< 100 mA + 10% of pulse amplitude
amplitude	0-25 A (loads 1 - 10 ohm)
peak current	25 A per channel
DC current limit	150 mA (each channel)
GENERAL	
weight	10 lbs.
power	<100 W @ 120 or 220 VAC
communications	R\$232
OPTIONS	
G GPIR Interface	

G - GPIB Interface

*Contact us for other options for amperage and pulse widths.

Fax



Email Web