

## 83651A Synthesized Sweeper, 45 MHz to 50 GHz

**Data Sheet** 

**Product Specifications** 

Specifications are the Agilent 8510 specifications, plus the following: Range: 45 MHz to 50 GHz **Resolution:** 1 Hz Accuracy CW Mode: Same as time base Swept Mode At Frequencies <=26.5 GHz Sweep Widths <=n x 10 MHz: 0.1% of sweep width ± time base accuracy Sweep Widths <n x 10 MHz and <=400 MHz: 1% of sweep width Sweep Widths <400 MHz and <=4 GHz: 4 MHz Sweep Widths >4 GHz: 0.1% of sweep width At Frequencies >26.5 GHz Sweep Widths <=n x 10 MHz: 0.1% of sweep width ± time base accuracy Sweep Widths >n x 10 MHz and <=800 MHz: 1% of sweep width Sweep Widths >800 MHz and <=8 GHz: 8 MHz Sweep Widths >8 GHz: 0.1% of sweep width **Output Power Specifications** Maximum Leveled Frequencies <=20 GHz: +10 dBm Frequencies >20 GHz and <=26.5 GHz: +4 dBm Frequencies >26.5 GHz and <=40 GHz: +3 dBm Frequencies >40 GHz: 0 dBm MinimumSettable: -20 dBm



## www.valuetronics.com